

## Technische Daten

### SABA Meersburg Automatic 11 Stereo

<b>Netzanschluß</b>	110/125/150/220 V, 50 Hz, max. 90 W
<b>Röhren, Gleichrichter</b>	EC 92, EC 92, ECH 81, EF 85, EABC 80, 2 x ECL 86, EM 84, EABC 80, ECL 80, B 250 C 125, E 12,5 C 5, E 62,5 C 5, RL 232
<b>Beleuchtungslampen</b>	2 Lampen 7 V/0,3 A (E 10) 5 Lampen 7 V/0,1 A (E 10) 6 Lampen 8,5 V/0,15 A (E 5,5)
<b>Sicherung</b>	T 0,9 A bei 110-150 V T 0,6 A bei 220 V
<b>Kreise</b>	FM 11 AM 8
<b>Wellenbereiche</b>	UKW 87 — 100 MHz KW 5,9 — 18,9 MHz MW 510 — 1640 kHz LW 140 — 360 kHz
<b>Zwischenfrequenz</b>	FM 6,75 MHz AM 460 kHz
<b>Ausgangsleistung</b>	MONO 8 W STEREO 2 x 4 W
<b>Lautsprecher</b>	2 x 18 x 24 cm 2 x 11,5 x 17 cm
<b>Gehäusemaße</b>	64 x 39,5 x 29 cm
<b>Gewicht</b>	18 kg netto 20 kg brutto
<b>Besonderheiten</b>	SABA-Motorelektronik

### SABA 300 Automatic Stereo 11

Technische Daten wie **Meersburg 11**, jedoch:

<b>Netzanschluß</b>	115 V, 60 Hz, max. 90 W
<b>Wellenbereiche</b>	UKW 88 — 108 MHz KW 5,9 — 18,9 MHz Marine 1,55 — 4,3 MHz MW 510 — 1640 kHz

### SABA Breisgau Automatic 11 Stereo

Technische Daten wie **Meersburg 11**, jedoch:

<b>Lautsprecher</b>	2 x 24 cm Ø 2 x 8 x 15 cm
<b>Gehäusemaße</b>	146,5 x 82,5 x 41 cm
<b>Gewicht</b>	61 kg netto 71 kg brutto
<b>Plattenwechsler</b>	DUAL 1008
<b>Besonderheiten</b>	Einstellmöglichkeit für Tonbandgerät. Die Truhe kann mit dem Nachhallgerät SABA SONORAMA ausgerüstet werden

### SABA Breisgau Automatic 12 Stereo

Technische Daten wie **Breisgau 11**, jedoch:

<b>Wellenbereiche</b>	UKW 87 — 104 MHz
-----------------------	------------------

## Technical Data

### SABA Meersburg Automatic 11 Stereo

<b>Power supply</b>	110/125/150/220 volts, 50 cps, max. 90 watts
<b>Tubes, rectifiers</b>	EC 92, EC 92, ECH 81, EF 85, EABC 80, 2 x ECL 86, EM 84, EABC 80, ECL 80, B 250 C 125, E 12.5 C 5, E 62.5 C 5, RL 232
<b>Illumination</b>	2 lamps 7 volts/0.3 amp. (E 10) 5 lamps 7 volts/0.1 amp. (E 10) 6 lamps 8.5 volts/0.15 amp. (E 5.5)
<b>Fuse</b>	T 0.9 amp. for 110-150 volts T 0.6 amp. for 220 volts
<b>Circuits</b>	FM 11 AM 8
<b>Tuning ranges</b>	FM 87 — 100 Mc SW 5.9 — 18.9 Mc BC 510 — 1640 kc LW 140 — 360 kc
<b>Intermediate frequ.</b>	FM 6.75 Mc AM 460 kc
<b>Power output</b>	MONO 8 watts undistorted STEREO 2 x 4 watts undistorted
<b>Loudspeakers</b>	2 x 18 x 24 cm (7" x 9 1/2") 2 x 11.5 x 17 cm (4 1/2" x 6 3/4")
<b>Cabinet dimensions</b>	64 x 39.5 x 29 cm 25 1/4" x 15 1/2" x 11 1/2"
<b>Weight</b>	18 kg (39 1/2 lbs.) net 20 kg (44 lbs.) gross
<b>Specialties</b>	SABA Motor electronic

### SABA 300 Automatic Stereo 11

Technical data like **Meersburg 11** but:

<b>Power supply</b>	115 volts, 60 cps, max. 90 watts
<b>Tuning ranges</b>	FM 88 — 108 Mc SW 5.9 — 18.9 Mc Marine 1.55 — 4.3 Mc BC 510 — 1640 kc

### SABA Breisgau Automatic 11 Stereo

Technical data like **Meersburg 11** but:

<b>Loudspeakers</b>	2 x 24 cm (9 1/2") Ø 2 x 8 x 15 cm (3 1/4" x 6")
<b>Cabinet dimensions</b>	146.5 x 82.5 x 41 cm 57 1/2" x 32 1/2" x 16"
<b>Weight</b>	61 kg (134 lbs.) net 71 kg (156 lbs.) gross
<b>Record changer</b>	DUAL 1008
<b>Specialties</b>	A tape recorder can be put in. The console can be adapted with reverberation (SABA SONORAMA)

### SABA Breisgau Automatic 12 Stereo

Technical data like **Breisgau 11** but:

<b>Tuning ranges</b>	87 — 104 Mc
----------------------	-------------